

UL Labeling Requirement

As required by UL standards, installation of this emergency driver mandates the application of the provided Luminaire Modification Label. This label includes the following statement :

“This equipment has more than one power supply connection point.”

The label must be affixed to the fixture housing during installation to indicate the presence of multiple power sources and to ensure compliance with safety and inspection requirements.

What's included

ITEM	QUANTITY
LED Emergency Driver	1
Installation Instruction	1
Test Button	1
Test button panel	1

PLEASE READ CAREFULLY AND FOLLOW ALL INSTRUCTIONS FOR YOUR OWN SAFETY

WARNING:

Disconnect both normal and emergency power supplies before installation.

Please read the following instructions applicable to these models.

Make sure all connections are in accordance with the National Electrical Code or Canadian Electrical Code and any local regulations.

CAUTION: Installation is to be performed only by qualified personnel.

CAUTION: This product is for use in indoor fixtures only. Do NOT use near heated air handling outlets, wet locations or hazardous locations.

CAUTION: An unswitched Ac power source is required (100-277/347VAC, 50/60 Hz)

CAUTION: Do not install near gas or electric heaters.

CAUTION: The use of accessory equipment not recommended by the manufacturer may cause an unsafe condition.

CAUTION: Do not use this product for other than intended use.

CAUTION: The equipment is intended for ordinary locations and for permanent installation into one or more listed emergency luminaires.

CAUTION: Equipment should be mounted in locations and at heights where it will not be subjected to tampering by unauthorized personnel.

CAUTION: Use with grounded, UL Listed, damp location rated fixtures and case should be grounding.

CAUTION: Due to sharp edges, handle with care.

CAUTION: Do not attempt to service the battery. A sealed, no-maintenance battery is used that is not field replaceable. Contact the manufacturer for information on service.

IMPORTANT: Please charge the battery consistently for >24 hours for the first time usage so as to activate the whole battery cells of discharging/charging duration.

IMPORTANT: The products are produced with built-in batteries, which could be stocked for one year at most without being used.

DISCLAIMER OF LIABILITY: STREAMER Solutions assumes no liability for damages or losses of any kind that may arise from the improper, careless, or negligent installation, handling or use of this product.

NOTICE: Fixture may become damaged and/or unstable if not installed properly.

IMPORTANT: Emergency lighting is a crucial life safety system , Testing must be performed after installation.

STREAMER
The Emergency Lighting Expert

Model No.:	Rated Input	Rated Output	Battery Pack	Duration
YH29F-16VN	100-347Vac,50/60Hz	DC150-220V 12.4W c.p	Ni-Cd 12V 2.8Ah 33.6Wh	>90 minutes
YH29FA-16VN	100-277Vac,50/60Hz	DC150-220V 12.4W c.p	Ni-Cd 12V 2.8Ah 33.6Wh	>90 minutes
YH29FA-21VL	100-277Vac,50/60Hz	DC200V 20.4W c.p	LiFePO ₄ 16V 3.3Ah 52.8Wh	>90 minutes
YH29F-25VL	100-347Vac,50/60Hz	DC150-220V 23W c.p	LiFePO ₄ 12.8V 4.5Ah 57.6Wh	>90 minutes
YH29FA-25VL	100-277Vac,50/60Hz	DC150-220V 23W c.p	LiFePO ₄ 12.8V 4.5Ah 57.6Wh	>90 minutes
YH29F-40WL	100-347Vac,50/60Hz	DC200V 34.6W c.p	LiFePO ₄ 12.8V 6.6Ah 84.48Wh	>90 minutes
YH29FA-40WL	100-277Vac,50/60Hz	DC200V 34.6W c.p	LiFePO ₄ 12.8V 6.6Ah 84.48Wh	>90 minutes

Technical drawing of the 1000mm long cable gland assembly, showing top and side views with dimension labels:

- Conduit length**: Dimension for the braided shield length.
- Length**: Dimension for the total length of the assembly.
- Width**: Dimension for the width of the main body.
- Mounting hole spacing**: Dimension for the distance between mounting holes.
- Height**: Dimension for the height of the main body.

Model No.:	Length	Width	Height	Mounting Spacing	Conduit length
YH29F(A)Series	13"(330mm)	2 3/5"(67mm)	2 1/5"(55mm)	12 2/5"(315.5mm)/1 4/5"(45mm)	11 4/5"(300mm)
YH29FA-21VL	13"(330mm)	3 "(75mm)	1 2/5"(35mm)	12 2/5"(315mm)/1 4/5"(45mm)	11 4/5"(300mm)

Wiring diagram for the YH29F(A) Series LED driver. The diagram shows the connection of AC Line (24/7), AC Line Switch, Neutral, Ground, Dimming input (+/-), and various output wires (Purple/White+, Pink/White-, Brown, Blue, Orange-, Gray+) to the LED Load and LED Driver. A test button and LED indicator are also shown.